MINIATURE RELAY

1 POLE—1 to 2 A (FOR SIGNAL SWITCHING) **FBR211 SERIES**

RoHS compliant

FEATURES

- 2 A maximum carrying current Capable of 2 A maximum continuous carrying current in the contact
- Superior reliability gold-overlay contacts P type: Gold-overlay silver-palladium contacts
- International terminal pitch of one inch grid terminal layout
- · High sensitivity, low power dissipation types also available Standard types: 0.45 W (A or B type) High sensitivity types: 0.2 W (C or E type)
- Conforms to FCC 68.302 (high dielectric strength type)
- UL recognized (File number E63615)
- CSA recognized (File number LR64026)
- RoHS compliant since date code: 0433A Please see page 5 for more information



ORDERING INFORMATION

(a)

[Example]

FBR211 S A D012 (b) (c) (d) (e)

(-CSA) (f) (g) (h)

[Exam	ple] (a) (b) (c) (d) ((e) (f) (g) (h)				
(a)	Series Name	FBR211				
(b)	Enclosure	S: Flux free type N: Plastic sealed type				
(c)	Coil Power and Schematics	A: Standard A type B: Standard B type C: High sensitivity C type E: High sensitivity E type				
(d)	Nominal Voltage	(Example) D003: 3 VDC D012: 12 VDC (refer to the COIL DATA CHART)				
(e)	UL Marking on Cover	Nil:No UL marking U :UL marking				
(f)	Contact Material P : Gold-overlay silver-palladium M : Gold-overlay silver					
(g)	Special Type	Nil : Standard 2 : High dielectric strength type				
(h)	CSA Marking Nil : Standard -CSA : UL + CSA marking (valid when (e) is U)					

Note: The designation name is stamped on the top of the relay case as follows: (Example) Designation ordered: FBR211SAD005-P

Stamp: 211SAD005-P

COIL DATA CHART

1. STANDARD (A or B type)

MODEL				Nominal	Coil	Nominal current	Must	Must	Maximum	Nominal	Coil
A type		B type		voltage	resistance (±10%)			release voltage	allowable	power	temperature
Flux free	Plastic sealed	Flux free	Plastic sealed	0	(=1070)	approx.	Voltago	Voltago	Voltago	•	1100
FBR211SAD001-n	FBR211NAD001-n	FBR211SBD001-n	FBR211NBD001-n	1.5 VDC	5 Ω	300 mA					
FBR211SAD003-n	FBR211NAD003-n	FBR211SBD003-n	FBR211NBD003-n	3 VDC	20 Ω	150 mA			150% of nominal voltage		Approx. 45 deg (at nominal voltage)
FBR211SAD005-n	FBR211NAD005-n	FBR211SBD005-n	FBR211NBD005-n	5 VDC	56 Ω	89 mA					
FBR211SAD006-n	FBR211NAD006-n	FBR211SBD006-n	FBR211NBD006-n	6 VDC	80 Ω	75 mA					
FBR211SAD009-n	FBR211NAD009-n	FBR211SBD009-n	FBR211NBD009-n	9 VDC	180 Ω	50 mA			vollage		
FBR211SAD012-n	FBR211NAD012-n	FBR211SBD012-n	FBR211NBD012-n	12 VDC	320 Ω	38 mA					
FBR211SAD024-n	FBR211NAD024-n	FBR211SBD024-n	FBR211NBD024-n	24 VDC	1,280 Ω	19 mA					

Note: All values in the table are measured at 20°C.

2. HIGH SENSITIVITY (C or E type)

MODEL				Nominal	Coil	Nominal current	Must	Must	Maximum	Nominal	Coil
C type		E type		voltage	resistance (±10%)	(at nominal voltage)		release	allowable	power	temperature
Flux free	Plastic sealed	Flux free	Plastic sealed	J	(±1070)	approx.	vonage	voltage	voltage	P	1130
FBR211SCD001-n	FBR211NCD001-n	FBR211SED001-n	FBR211NED001-n	1.5 VDC	12 Ω	125 mA					
FBR211SCD003-n	FBR211NCD003-n	FBR211SED003-n	FBR211NED003-n	3 VDC	45 Ω	67 mA					
FBR211SCD005-n	FBR211NCD005-n	FBR211SED005-n	FBR211NED005-n	5 VDC	120 Ω	42 mA	70% max.	10% min.	225% of	Approv	Approx
FBR211SCD006-n	FBR211NCD006-n	FBR211SED006-n	FBR211NED006-n	6 VDC	180 Ω	33 mA	of nominal voltage	of nominal voltage	nominal voltage	Approx. 200 mW (at nominal	Approx. 25 deg (at nominal
FBR211SCD009-n	FBR211NCD009-n	FBR211SED009-n	FBR211NED009-n	9 VDC	400 Ω	23 mA	voltage	voltage	voltage	voltage)	voltage)
FBR211SCD012-n	FBR211NCD012-n	FBR211SED012-n	FBR211NED012-n	12 VDC	700 Ω	17 mA					
FBR211SCD024-n	FBR211NCD024-n	FBR211SED024-n	FBR211NED024-n	24 VDC	2,800 Ω	9 mA					
Note: All va	lues in the tal	ble are meas	ured at 20°C					1	U		

SPECIFICATIONS

Item			Standard (A or B type)	High sensitive (C or E type)			
Contact	Arrangement		1 form C (SPDT)				
	Material		Gold-overlay silver-palladium / gold-overlay silver				
	Resistance (initial)		Maximum 100 mΩ (at 0.1 A 6 VDC)				
	Rating (resistive)		0.5 A 120 VAC or 1 A 28 VDC				
	Maximum Carrying Current		2 A				
	Maximum Switching Power		60 VA or 28 W				
	Max. Switch	ing Voltage*1	220 VAC or 150 VDC				
	Maximum Switching Current		1.25 A (AC) or 2 A (DC)				
	Minimum Switching load* ² (reference)		Plastic sealed 1 mA, 1V Flux free 1 mA, 5V				
Coil	Nominal Power (at 20°C)		Approximately 450 mW	Approximately 200 mW			
	Operate Power (at 20°C)		Approximately 315 mW maximum	Approximately 140 mW maximum			
	Operating Temperature		–25°C to +55°C (no frost)	–25°C to +75°C (no frost)			
	Operating Humidity		45 to 85%RH				
Time Value	Operate (at nominal voltage)		Maximum 5 ms				
	Release (at nominal voltage)		Maximum 5 ms				
Life	Mechanical		5 × 10 ⁶ operations minimum				
	Electrical (Refer to the REFERENCE DATA)		3×10^{5} operations minimum (at 1 A/ 28 VDC resistive load) 1×10^{5} operations minimum (at 2 A/ 12 VDC resistive load) 1×10^{5} operations minimum (at 0.5 A/120 VDC resistive load)				
Other	Vibration Resistance		10 to 55 Hz (double amplitude of 1.5 mm)				
	Shock Resistance	Misoperation	100 m/s² (11± ¹ ms)	60 m/s² (11± ¹ ms)			
	Tresistance	Endurance	1,000 m/s² (11± ¹ ms)				
	Weight		Approximately 4 g				

*1 If the switching voltage exceeds the rated contact voltage, reduce the current. The current values vary according to the type of load.

*2 Values when switching a resistive load at normal room temperature and humidity and in a clean environment. The minimum switching load varies with the switching frequency and operation environment.

■ INSULATION

Item		Standard (A or B) High sensitive (C or E)			
Isolation (initial)		Minimum 100 MΩ (at 500VDC)			
Dielectric		500VAC 1 min. (standard)			
Strength		1,500VAC 1 min. (high isolation of	coil and contact)		

SAFETY STANDARDS

Туре	Compliance	Contact rating
UL	UL 110 E63615	Flammability: UL 94-V0 (plastics) 0.5A, 120VAC (resistive)
CSA	C22.2 No. 14 LR 40304, LR 46016	1A, 28VDC (resistive)



DIMENSIONS







2. N-TYPE (Plastic sealed type)

•Dimensions





Schematics (BOTTOM VIEW)

(A type or C type)

(B type or E type)





3. PC BOARD MOUNTING HOLE LAYOUT

•PC board mounting hole layout (BOTTOM VIEW)



Unit: mm

RoHS Compliance and Lead Free Relay Information

1. General Information

- Relays produced after the specific date code that is indicated on each data sheet are lead-free now. Most of our signal and power relays are lead-free. Please refer to Lead-Free Status Info. (http://www.fujitsu.com/us/downloads/MICRO/fcai/relays/lead-free-letter.pdf)
- Lead free solder paste currently used in relays is Sn-3.0Aq-0.5Cu. ٠
- All signal and most power relays also comply with RoHS. Please refer to individual data sheets. Relays that are RoHS compliant do not contain the 5 hazardous materials that are restricted by RoHS directive (lead, mercury, chromium IV, PBB, PBDE).
- It has been verified that using lead-free relays in leaded assembly process will not cause any • problems (compatible).
- "LF" is marked on each outer and inner carton. (No marking on individual relays).
- To avoid leaded relays (for lead-free sample, etc.) please consult with area sales office.
- We will ship leaded relays as long as the leaded relay inventory exists.

Note: Cadmium was exempted from RoHS on October 21, 2005. (Amendment to Directive 2002/95/EC)

2. Recommended Lead Free Solder Profile

Recommended solder paste Sn-3.0Ag-0.5Cu.

Reflow Solder condition

Flow Solder condition:

Pre-heating: maximum 120°C Soldering: dip within 5 sec. at 260°C soler bath

Solder by Soldering Iron:

Soldering Iron Temperature: maximum 360°C Duration: maximum 3 sec.

We highly recommend that you confirm your actual solder conditions

3. Moisture Sensitivity

Moisture Sensitivity Level standard is not applicable to electromechanical realys.

4. Tin Whisker

Dipped SnAgCu solder is known as low risk tin whisker. No considerable length whisker was found by our in house test.

FBR211 SERIES

Fujitsu Components International Headquarter Offices

Japan Fujitsu Component Limited	Europe Fujitsu Components Europe B.V.
Gotanda-Chuo Building	Diamantlaan 25
3-5, Higashigotanda 2-chome, Shinagawa-ku	2132 WV Hoofddorp
Tokyo 141, Japan	Netherlands
Tel: (81-3) 5449-7010	Tel: (31-23) 5560910
Fax: (81-3) 5449-2626	Fax: (31-23) 5560950
Email: promothq@ft.ed.fujitsu.com	Email: info@fceu.fujitsu.com
Web: www.fcl.fujitsu.com	Web: emea.fujitsu.com/components/
North and South America	Asia Pacific
Fujitsu Components America, Inc.	Fujitsu Components Asia Ltd.
250 E. Caribbean Drive	102E Pasir Panjang Road
Sunnyvale, CA 94089 U.S.A.	#01-01 Citilink Warehouse Complex
Tel: (1-408) 745-4900	Singapore 118529
Fax: (1-408) 745-4970	Tel: (65) 6375-8560
Email: components@us.fujitsu.com	Fax: (65) 6273-3021
Web: http://www.fujitsu.com/us/services/edevices/components/	Email: fcal@fcal.fujitsu.com
	Web: http://www.fujitsu.com/sg/services/micro/components/

©2009 Fujitsu Components America, Inc. All rights reserved. All trademarks or registered trademarks are the property of their respective owners.

Fujitsu Components America or its affiliates do not warrant that the content of datasheet is error free. In a continuing effort to improve our products Fujitsu Components America, Inc. or its affiliates reserve the right to change specifications/datasheets without prior notice. Rev. June 30, 2009.