

## **KSB834**

# Low Frequency Power Amplifier

Complement to KSD880



1.Base 2.Collector 3.Emitter

## **PNP Silicon Epitaxial Transistor**

## Absolute Maximum Ratings $T_C=25^{\circ}C$ unless otherwise noted

Symbol	Parameter	Value	Units
$V_{CBO}$	Collector-Base Voltage	- 60	V
V <sub>CEO</sub>	Collector-Emitter Voltage	- 60	V
V <sub>EBO</sub>	Emitter-Base Voltage	- 7	V
I <sub>C</sub>	Collector Current	- 3	Α
I <sub>B</sub>	Base Current	- 0.5	Α
P <sub>C</sub>	Collector Dissipation (T <sub>C</sub> =25°C)	30	W
P <sub>C</sub>	Collector Dissipation (T <sub>a</sub> =25°C)	1.5	W
T <sub>J</sub>	Junction Temperature	150	°C
T <sub>STG</sub>	Storage Temperature	- 55 ~ 150	°C

### **Electrical Characteristics** $T_C=25$ °C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
I <sub>CBO</sub>	Collector Cut-off Current	$V_{CB} = -60V, I_{E} = 0$			- 100	μΑ
I <sub>EBO</sub>	Emitter Cut-off Current	$V_{EB} = -7V, I_{C} = 0$			- 100	μΑ
BV <sub>CEO</sub>	Collector-Emitter Breakdown Voltage	$I_C = -50 \text{mA}, I_B = 0$	- 60			V
h <sub>FE1</sub>	DC Current Gain	$V_{CE} = -5V, I_{C} = -0.5A$ $V_{CE} = -5V, I_{C} = -3A$	60 20		200	
V <sub>CE</sub> (sat)	Collector-Emitter Saturation Voltage	$I_C = -3A, I_B = -0.3A$		- 0.5	- 1	V
V <sub>BE</sub> (on)	Base-Emitter ON Voltage	$V_{CE} = -5V, I_{C} = -0.5A$		- 0.7	- 1	V
f <sub>T</sub>	Current Gain Bandwidth Product	$V_{CE} = -5V, I_{C} = -0.5A$		9		MHz
C <sub>ob</sub>	Output Capacitance	V <sub>CB</sub> = - 10V, I <sub>E</sub> = 0 f = 1MHz		150		pF
t <sub>ON</sub>	Turn ON Time	$V_{CC} = -30V, I_{C} = -1A$		0.4		μs
T <sub>STG</sub>	Storage Time	$I_{B1} = -I_{B2} = -0.2A$		1.7		μs
t <sub>F</sub>	Fall Time	$R_L = 30\Omega$		0.5		μs

## **h**<sub>FE</sub> Classification

Classification	0	Y
h <sub>FE1</sub>	60 ~ 120	100 ~ 200

# **Typical Characteristics**




Figure 1. Static Characteristic





Figure 2. DC current Gain



Ic(A), COLLECTOR CURRENT




Figure 4. Base-Emitter On Voltage

Figure 3. Collector-Emitter Saturation Voltage




Figure 5. Safe Operating Area






Figure 6. Power Derating

©2001 Fairchild Semiconductor Corporation Rev. A1, June 2001

# **Package Demensions**

# TO-220





10.00 ±0.20

#### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	FAST <sup>®</sup>	OPTOPLANAR™	STAR*POWER™
Bottomless™	FASTr™	PACMAN™	Stealth™
CoolFET™	FRFET™	POP™	SuperSOT™-3
$CROSSVOLT^{rM}$	GlobalOptoisolator™	Power247™	SuperSOT™-6
DenseTrench™	GTO™	PowerTrench <sup>®</sup>	SuperSOT™-8
DOME™	HiSeC™	QFET™	SyncFET™
EcoSPARK™	ISOPLANAR™	QS™	TruTranslation™
E <sup>2</sup> CMOS™	LittleFET™	QT Optoelectronics™	TinyLogic™
EnSigna™	MicroFET™	Quiet Series™	UHC™
FACT™	MICROWIRE™	SLIENT SWITCHER®	UltraFET <sup>®</sup>
FACT Quiet Series™	OPTOLOGIC™	SMART START™	VCX™

STAR\*POWER is used under license

#### **DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### **LIFE SUPPORT POLICY**

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

©2001 Fairchild Semiconductor Corporation Rev. H

This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.