The LA7850 is a sync deflection circuit IC dedicated to CRT display use. It can be connected to the LA7832,7833,7837.7838 (for vertical output use) to form a sync deflection circuit that meets every requirement for CRT display use.

So far, ICs for color TV use have been applied to the sync deflection circuit for CRT display use and general-purpose ICs such as one-shot multivibrator, inverter and a lot of transistors have been used to form the peripherals such as sync input interface, horizontal phase shifter. The LA7850 contains these peripherals on chip and adopts a stable circuit for horizontal oscillation from 15kHz to 100kHz aiming at improving the characteristics required for CRT display use.

Features

- The horizontal oscillation frequency can be adjusted stably from 15kHz to 100kHz.
- The horizontal display can be shifted right/left.
- The horizontal/vertical sync input can be used intact regardless of the difference in pulse polarity and pulse width.
- The AFC feedback sawtooth wave can be obtained by simply applying a flyback pulse to the IC as a trigger pulse.
- · Any duty of the horizontal pulse can be set.
- \cdot Good vertical linearity because DC bias at vertical output stage is subjected to sampling control within retrace time.

[Vertical Block]

Vertical OSC

 \cdot Vertical sawtooth wave generator

 \cdot Sampling type DC voltage control

1.2

On-chip Functions

[Horizontal Block]

- · AFC
- \cdot Horizontal OSC
- · X-ray protector
- · Horizontal phase shift
- · AFC sawtooth wave generator
- · Horizontal pulse duty setting



SANYO Electric Co., Ltd. Semiconductor Business Headquarters TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110 JAPAN

SANYO: DIP20Slim

LA7850

| ····· | | | | | |
|--|--------------------|---|------------|-----------|------------------------|
| Operating Conditions at Ta=25°C | | | | unit | |
| Recommended Supply Voltage | | V_{10}, V_{20} | | 12 V | |
| Operating Voltage Range | | V_{10}, V_{20} | 9 to 1 | .3.5 V | |
| Recommended Vertical Pulse Input | Peak Y | Value V _{pulse} | | 5 Vp-p | |
| Operating Vertical Pulse Input Peak Value Range V _{pulse} | | | | to6 Vp-p | |
| Recommended Horizontal Pulse Input Peak Value H _{nulse} | | | | 5 Vp-p | |
| Operating Horizontal Pulse Input Peak Value Range H _{pulse} | | | | to 6 Vp-p | |
| | | - | | | • |
| Operating Characteristics at Ta=2 | | $_{0},V_{20}=12V$ | min | typ max | unit |
| V _{CC10} Current Dissipation | I_{10} | | 12 | 30 | $\mathbf{m}\mathbf{A}$ |
| V _{CC20} Current Dissipation | I_{20} | | . 5 | 12 | $\mathbf{m}\mathbf{A}$ |
| Vertical Frequency Pull-in Range | $V_{p in}$ | Vertical sync 60Hz | 10.0 | 12.0 | Hz |
| Vertical Free-running Frequency | f _v | f _v center 55 Hz | 50 | 60 | Hz |
| Increased/Reduced Voltage | Δf_{vv} | $V_{20} = 12 \pm 1V,55$ Hz at 12V | -0.1 | 0.1 | Hz |
| Characteristic of Vertical Frequenc | у | | | | |
| Midpoint Control Threshold Level | | | 3.8 | 4.4 | v |
| Vertical OSC Start Voltage | $\mathbf{f_{vst}}$ | | | 4.0 | v |
| Temperature Characteristic of | | $Ta = -10 \text{ to } + 60^{\circ}C$ | -0.028 | 0.028 | Hz/°C |
| l Vertical Frequency | | | | | |
| Vertical Driver | Gv | | 12 | 18 | dB |
| Amplification Factor | | | | | |
| Horizontal AFC DC Loop Gain | I _{AFC} | | ± 0.85 | ±1.6 | mA |
| Horizontal Free-running Frequency | r f _H | f _H center 15.734kHz | -750 | 750 | Hz |
| Horizontal OSC Start Voltage | f _{H st} | | | 4.0 | v |
| (Increased/Reduced Voltage | | $V_{10} = 12 \pm 1V, 15.734$ kHz at 12V | -50 | 50 | Hz |
| Characteristic of Horizontal Freque | | | | | |
| fHorizontal OSC Warm-up Drift | Δf_{H} | 5s. to 30min. | -50 | 50 | Hz |
| | | after application of power | | | |
| Temperature Characteristic of | | Ta = -10 to $+60$ °C | -2.9 | 2.9 | Hz/°C |
| Horizontal Frequency | | | | | |
| Horizontal Output Drive Current | I ₁₂ | | 6.0 | 12.0 | mA |
| [Increased/Reduced Voltage | | $V_{10} = 12 \pm 1V$ | -0.5 | 0.5 | %/V |
| Characteristic of Phase Shifter | | 10 | | | |
| Delay Time | | | | | |
| Temperature Characteristic of | | $Ta = -10 \text{ to } + 60^{\circ}C$ | -0.1 | 0.1 | %/°C |
| Phase Shifter Delay Time | | | • | | |
| [Increased/Reduced Voltage | | $V_{10} = 12 \pm 1 V$ | -1.0 | 1.0 | %/V |
| Characteristic of Phase Shifter | | 10 | | | |
| Delay Time | | | | | |
| Temperature Characteristic of | | $Ta = -10$ to $+60^{\circ}C$ | -0.13 | 0.13 | %/°C |
| Phase Shifter Pulse Width | | | | | |
| AFC Phase Comparison Center Tim | ie | 15.734kHz after F.B.P. input | 9.9 | 11.5 | μs |
| [Increased/Reduced Voltage | | $V_{10} = 12 \pm 1V$ | -1.5 | 1.5 | - |
| Characteristic of AFC Phase | | 10 == = = 1 | | 210 | 101 1 |
| Comparison Center Time | | · | | | |
| Temperature Characteristic of | | $Ta = -10 \text{ to } + 60^{\circ}C$ | -0.2 | 02 | %/°C |
| AFC Comparison Center Time | | | 0.2 | 0.2 | |
| Comparison Waveform Generating | V٨ | | 0.6 | 0.9 | v |
| Input Operation Voltage | * * | | 0.0 | . 0.0 | Ŧ |
| [Pin 13 Voltage at Hold-down | V ₁₃ | | 0.5 | 0.8 | v |
| Operation Start | . 19 | | 0.0 | 0.0 | ¥ |
| - For account to start a | | | | | |



Sample Application Circuit: 14 "Color Monitor/ $f_V = 60$ Hz, $f_H = 15.734$ kHz



No.1581-3/5



Sample Application Circuit: 14" Color Moniror/ $f_V = 60$ Hz, $f_H = 15.734$ kHz

LA7850 Family

| | Type No. | LA7850 | LA7851 | LA7852 | LA7853 |
|--------------------------------|--|------------------------|------------------------|--------------------------|--------------------------|
| | Package ' | DIP-20S (Slim Type) | DIP-20S (Slim Type) | DIP-22S (Shrink Type) | DIP-22S (Shrink Type) |
| Differences characteristics | Vertical pull-in range (f _v = 60Hz) | 10Hz | 20Hz | 10Hz | 20Hz |
| Dit in cha | GND pin | Hor./vert. common | Hor /vert. | Hor./vert. separated | Hor./vert. separated |

- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall: ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of June, 1996. Specifications and information herein are subject to change without notice.